DESCRIPTION

MULTIMODE DIELECTRIC RESONATOR DEVICE, DIELECTRIC FILTER,

COMPOSITE DIELECTRIC FILTER AND COMMUNICATION APPARATUS

5   Technical Field

This invention relates to a dielectric resonator device

operating in a multimode, and a dielectric filter, a

composite dielectric filter and a communication apparatus

which include the same.

10

Background Art

Previously, Japanese Unexamined Patent Application

Publication No. 11-145704 has disclosed a multimode

dielectric resonator device having a dielectric core

15   disposed in a cavity and using a plurality of TM modes and

TE modes.

In this multimode dielectric resonator device, when

coupling is performed between predetermined modes by the

shape of the dielectric core, perturbation on an electric

20   field is performed by providing a groove or a hole at a

portion on which electric fields to be coupled are

concentrated in order to exchange energy between the

resonance modes, thereby the coupling is performed.

However, in a known multimode dielectric resonator

25   device, there has been a problem in that coupling is also

1

produced between the TM mode and the TM mode at the same

time even if the shape of the dielectric core is determined

only by paying attention to the portion on which two modes

of electric fields to be coupled are concentrated in order

5   to perform the coupling between the TE mode and the TE mode.

For example, when coupling is performed between an

TE01δ_x mode in which an electric field is rotated in a

plane perpendicular to an x-axis and an TE01δ_y mode in

which an electric field is rotated in a plane perpendicular

10   to a y-axis in an x-y-z rectangular cartesian coordinate

system, a groove and a hole are provided at the portions

through which the electric flux of an even mode and an odd

mode, which are a coupling mode of both modes, pass in order

to make a difference between the resonant frequencies of the

15   even mode and the odd mode. Thereby, it is possible to

couple the two TE modes described above with each other.

However, the groove and the hole described above cause

perturbation to arise between an TM01δ-x mode in which an

electric field is directed in an x direction and an TM01δ-y

20   mode in which an electric field is directed in a y direction,

and thus these two TM modes are coupled with each other.

That is to say, in a multimode dielectric resonator using

both the TM mode and the TE mode, when the coupling between

the TE mode and the TE mode is performed, the coupling

25   between the TM mode and the TM mode is also caused to arise,

2

and thus it is difficult to independently determine the amount of coupling between the TE mode and the TE mode.

Also, if a dielectric core is provided with a groove or has a shape with a protruding part in order to perform
5   coupling between the TE mode and the TE mode, the shape of the electric flux distribution is disarranged. As a result, the frequency of the basic mode increases or decreases. Thus, there has been a problem in that when a filter is constructed by coupling a plurality of resonant modes in
10   sequence, the difficulty in adjusting the filter characteristics thereof increases.

Accordingly, an object of this invention is to provide a multimode dielectric resonator device which couples two TE modes, whose electric-field rotating planes have a
15   perpendicular relationship, independently of the coupling between two TM modes whose electric-field directions have the same perpendicular relationships, respectively.

Also, another object of this invention is to couple the TE modes themselves while avoiding coupling of the TM modes
20   having the relationship described above and to provide a multimode dielectric resonator device equipped with four-stage resonators of TM-mode-TE-mode-TE-mode-TM-mode by coupling the TM mode and the TE mode of the one side and coupling the TM mode and the TE mode of the other side, and
25   furthermore another object of this invention is to provide a

3

dielectric filter, a composite dielectric filter, and a
communication apparatus including the above-described device.

Disclosure of Invention

5   According to this invention, there is provided a
multimode dielectric resonator device having a dielectric
core disposed in a cavity, for producing a first $TM01\delta$ mode
or $TM011$ mode having an electric field directed in a first
direction, a second $TM01\delta$ mode or $TM011$ mode having an

10   electric field directed in a second direction perpendicular
to the first direction, a first $TE01\delta$ mode having an
electric field rotated in a plane perpendicular to the first
direction, and a second $TE01\delta$ mode having an electric field
rotated in a plane perpendicular to the second direction,

15   respectively,

       wherein the effective dielectric constants of
individual dielectric core portions having electric flux of
an even-mode and an odd-mode of TE coupling mode in the
first and the second $TE01\delta$ modes passing through are

20   different from each other, and the effective dielectric
constants of individual dielectric core portions having
electric flux of an even-mode and an odd-mode of TM coupling
mode in the first and the second $TM01\delta$ mode or $TM011$ mode
passing through are substantially equal.

25   Accordingly, a difference in frequency arises between

4

the even-mode and the odd-mode, which are two coupling modes
of the first and the second $TE01\delta$ modes, and thus the first
and the second $TE01\delta$ modes are coupled. Also, no difference
in frequency arises between the even-mode and the odd-mode,

5   which are two coupling modes of the first and the second
$TM01\delta$ modes or $TM011$ modes, and thus the first and the
second $TM01\delta$ modes or $TM011$ modes are not coupled with each
other. That is to say, the coupling between the first and
the second $TE01\delta$ modes can be set independently from the

10   coupling of $TM01\delta$ or $TM011$ modes.

Also, in this invention, there is provided a difference
in the amount of protrusion or the amount of subsidence in
the dielectric core portions having electric flux passing
therethrough with regard to the even mode and odd mode of

15   the TE coupling mode, and a subsidence or protrusion for
canceling frequency changes of the even mode and the odd
mode of the TM coupling mode, by said difference of the
amount of the protrusion or the amount of the subsidence, is
disposed on the dielectric core portion of said TE coupling

20   mode having a relatively small electric flux density.

With this structure, a frequency change in the even
mode and the odd mode of the TM coupling mode, which arises
by the difference in the amount of protrusion or the amount
of subsidence of the dielectric core disposed on the

25   position having a high electric flux density of the TE

5

coupling mode, is canceled, and thus the coupling between the first and the second $TM01\delta$ modes or $TM011$ modes can be prevented.

Also, there is provided according to this invention a multimode dielectric resonator device equipped with four-stage resonators having a first $TM01\delta$ mode or $TM011$ mode, a first $TE01\delta$ mode, a second $TE01\delta$ mode, and a second $TM01\delta$ mode or $TM011$ mode by coupling the first and the second $TE01\delta$ modes with the first and the second $TM01\delta$ modes or $TM011$ modes, respectively, by displacing a center of electric flux density distribution of the first and the second $TM01\delta$ modes or the first and the second $TM011$ modes upward or downward in planes perpendicular to the directions of the electric fields of the first and the second $TM01\delta$ modes or the first and the second $TM011$ modes.

In this manner, the first and the second $TM01\delta$ modes or $TM011$ modes and the first and the second $TE01\delta$ modes are coupled, respectively, by displacing a center of electric flux density distribution of the first and the second $TM01\delta$ modes or the first and the second $TM011$ modes upward or downward in planes perpendicular to the directions of the electric fields of the first and the second $TM01\delta$ modes or the first and the second $TM011$ modes. At this time, the coupling does not arise between the first and the second $TM01\delta$ modes or the $TM011$ modes themselves, and thus an

6

operation is performed as four-stage resonators in which the first $TM01\delta$ mode or TM011 mode→the first $TE01\delta$ mode→the second $TE01\delta$ mode→the second $TM01\delta$ mode or TM011 mode are coupled in sequence.

5   Also, according to this invention, there is provided a dielectric filter including: a multimode dielectric resonator device operating as four-stage resonators described above; and external coupling means for external coupling in the first-stage and the last-stage resonators,

10   respectively, of the four-stage resonators.

Thereby, a filter including a band-pass characteristic including four-stage resonators operation is performed.

Also, there is provided according to this invention a composite dielectric filter including two sets of the

15   dielectric filters described above, sharing one of the external coupling means of each of the dielectric filters.

For example, an operation is performed as a transmitter/receiver by using one of the filters as a transmission filter, the other of the filters as a reception

20   filter, and the shared external coupling means as an antenna port.

Also, according to this invention, there is provided a communication apparatus equipped with the above-described dielectric filter or composite dielectric filter in its

25   high-frequency circuit portion.

7

Brief Description of the Drawings

Fig. 1 is a diagram illustrating directions of electric flux and magnetic flux of four resonant modes in the multimode dielectric resonator device according to a first embodiment. Fig. 2 is a diagram illustrating directions of the passing electric flux of each mode of the same dielectric resonator device. Fig. 3 is a diagram illustrating directions of the passing electric flux of each mode in a state in which a dielectric core 1 is contacted with the inner surface of a cavity 2. Fig. 4 is a diagram illustrating examples of the distribution of electric flux densities in the four resonant modes. Fig. 5 is a diagram illustrating a coupling sequence of the four resonant modes. Fig. 6 is a diagram illustrating a cross-sectional shape of each layer of the dielectric core in the cavity. Fig. 7 is a diagram illustrating the effect of a protrusion of the TE coupling on an TE coupling mode and an TM coupling mode. Fig. 8 is a diagram illustrating a relationship between the amount of protrusion of a protrusion portion P disposed in the dielectric core 1 and the resonant frequency and the coupling factor of each mode. Fig. 9 is a diagram illustrating relationships between the amount of protrusion of a protrusion portion P and the amount of subsidence of a subsidence portion S disposed in the dielectric core 1. Fig.

8

10 is a diagram illustrating the configuration of a
dielectric filter. Fig. 11 is a diagram illustrating the
configuration of a dielectric filter according to a second
embodiment. Fig. 12 is a diagram illustrating the
5   configuration of a dielectric filter according to a third
embodiment. Fig. 13 is a diagram illustrating the
configuration of another dielectric filter according to the
third embodiment. Fig. 14 is a diagram illustrating the
configuration of a dielectric filter according to a fourth
10   embodiment. Fig. 15 is a diagram illustrating the
configuration of another dielectric filter according to the
fourth embodiment. Fig. 16 is a diagram illustrating the
configuration of a dielectric filter according to a fifth
embodiment. Fig. 17 is a diagram illustrating the
15   configuration of another dielectric filter according to the
fifth embodiment. Fig. 18 is a diagram illustrating the
configuration of a dielectric filter according to a sixth
embodiment. Fig. 19 is a diagram illustrating the
configuration of a dielectric filter according to a seventh
20   embodiment. Fig. 20 is a diagram illustrating the
configuration of a dielectric filter according to an eighth
embodiment. Fig. 21 is a diagram illustrating the
configuration of a composite dielectric filter according to
a ninth embodiment. Fig. 22 is a block diagram illustrating
25   the configuration of a communication apparatus according to

9

a tenth embodiment.

Best Mode for Carrying Out the Invention

A description will be given of a multimode dielectric

5 resonator device according to a first embodiment with

reference to Figs. 1 to 10.

The material of the dielectric core disposed in the

devices shown in each embodiment including this first

embodiment is selected in accordance with the frequency band

10 used for the device. For example, a selection is made from

groups including zirconium titanate-stannum titanate series

compounds, rare-earth barium titanate series compounds,

barium titanate series compounds, zinc barium tantalate

series compounds, magnesium barium tantalate series

15 compounds, rare earth aluminate -calcium titanate series

compounds, magnesium titanate-calcium titanate series

compounds. The relative dielectric constant at this time

has an arbitrary value between 20 to 130. A zirconium

titanate-stannum titanate compound having a relative

20 dielectric constant of 38 is used in this first embodiment

and the other embodiments shown subsequently.

Fig. 1 is a perspective view showing a dielectric core

disposed in a cavity and the shapes of four resonant modes

to be used. A solid-line arrow in the figure indicates a

25 line of electric force and a broken-line arrow indicates a

10

line of magnetic force. (A) TM01δ_x mode, which is the first TM01δ mode, (B) TE01δ_y mode, which is the first TE01δ mode, (C) TE01δ_x mode, which is the second TE01δ mode, and (D) TM01δ_y mode, which is the second TM01δ mode, each of which shows the electromagnetic filed distributions using lines of electric force and lines of magnetic force.

Also, Fig. 2 shows electric flux density distribution of the four modes, including the cavity. Here, (A) is a view seen from z-axis direction. (B) is a view seen from y-axis direction. Also, the solid-line arrow indicates a line of electric force. In this manner, a dielectric core 1 is disposed inside cavity 2 having a substantially cubic shape.

In the TM01δ_x mode, an electric field is directed in the x direction and a magnetic field rotates in a plane parallel to the y-z plane. In this TM01δ_x mode, an electric field is mainly concentrated onto the 1x part, that is, an x-direction part of the dielectric core. The TM01δ_y mode is at a 90° rotated from the TM01δ_x mode around the z-axis. That is to say, an electric field is directed in the y direction and a magnetic field rotates in a plane parallel to the x-z plane which is perpendicular to the electric field. In this TM01δ_y mode, an electric field is mainly concentrated onto the 1y part, that is, an y-direction part of the dielectric core.

In the TE01δ_y mode, an electric field rotates in a

11

plane perpendicular to the y direction. In this TE01δ_y

mode, an electric field is mainly concentrated onto the 1x

part, that is, an x-direction part of the dielectric core.

The TE01δ_x mode is at a 90° rotated from the TE01δ_y mode

5   around the z-axis. That is to say, an electric field

rotates in a plane perpendicular to the x direction. In

this TE01δ_x mode, an electric field is mainly concentrated

onto the 1y part, that is, a y-direction part of the

dielectric core.

10   The portion denoted as "Pm" of the dielectric core 1 is

a protrusion protruding from the dielectric core 1 toward

the inner surface of the cavity 2. The electric flux of the

TM mode passes mainly through a capacity portion created

between the end face of this dielectric core protrusion Pm

15   and the inner surface of the cavity 2. That is to say, the

resonant frequency of the TM mode is determined by the

capacity created between the end face of this dielectric

core protrusion Pm and the inner surface of the cavity 2.

Also, independence of the electric flux of the TM mode

20   passing inside the dielectric core 1 is increased.

As described in detail below, when the TE01δ_y mode and

the TE01δ_x mode are coupled, the coupling between the

TM01δ_x mode and the TM01δ_y mode occurs simultaneously in

accordance with it.

25   Fig. 4 shows examples in which electric flux densities

12

of said four resonant modes are obtained by simulation. In
this manner, in the TM01δ_x mode, electric flux runs from
the inner surface of the cavity near one end face of the x-
direction portion 1x of the dielectric core to the inner

5   surface of the cavity near the other end face.

Fig. 3 is an example using another dielectric core 1.
Here, (A) is a view seen from the z-axis direction and (B)
is a view seen from the y-axis direction. In the examples
shown in Figs. 2 and 4, the TM01δ_x mode and the TM01δ_y mode

10   are produced by setting the end faces of the four sides of
the dielectric core 1 apart from the inner surface of the
cavity 2. However, as shown in Fig. 3, if the end faces of
the four sides of the dielectric core 1 are set in contact
with the inner surface of the cavity 2, it can be operated

15   as a TM011x mode and a TM011y mode.

Fig. 5 shows a coupling sequence of the four resonant
modes described above. In this example, the TM01δ_x mode
and the TE01δ_y mode are coupled, the TE01δ_y mode and the
TE01δ_x mode are coupled, and further the TE01δ_x mode and

20   the TM01δ_y mode are coupled. Also, at the same time, the
coupling between the TM01δ_x mode and the TM01δ_y mode is
caused not to occur.

Next, a structure for coupling the TE01δ_y mode and the
TE01δ_x mode without producing the coupling between the

25   TM01δ_x mode and the TM01δ_y mode is shown in Fig. 6. Here,

13

(D) is a side view seen in the y-axis direction, (A) is a sectional view seen on A-A part, (B) is a sectional view taken on B-B part, and (C) is a sectional view seen on C-C part. The dielectric core 1 basically has a three-layer

5   structure. (A), (B), and (C) are sectional views taken on an upper layer La, a middle layer Lb, and a lower layer Lc, respectively. In the upper layer La part, as shown in (A), protrusions Pe1 of the dielectric core protruding in the direction of x + y (in the direction having a direction

10   angle of 45° assuming that the x direction is 0 degree) and in the direction of -(x + y) (in the direction having a direction angle of -135° assuming that the x direction is 0 degree) are formed at the intersection between the x-direction part 1x and y-direction part 1y of the dielectric

15   core 1. Also, in the lower layer Lc part, as shown in (C), protrusions Pe2 are formed in the same direction. In the middle layer Lb part, as shown in (B), protrusions Pc protruding in the direction of y - x (in the direction having a direction angle of 135° assuming that the x

20   direction is 0 degree) and in the direction of x - y (in the direction having a direction angle of -45° assuming that the x direction is 0 degree) are formed, respectively.

Figs. 7(A) and 7(B) show electric flux density distribution of two coupling modes (TE coupling modes) by

25   the TE01δ_x mode and the TE01δ_y mode when the dielectric

14

core 1 having the structure shown in Fig. 6 is used. Figs.

7(A) and 7(B) show an even-mode electric flux density

distribution and an odd-mode electric flux density

distribution, respectively. In this case, the protrusions

5   Pe1 of the dielectric core operate to increase the effective

dielectric constant of the part through which an even-mode

electric flux passes. This also applies to the operation

provided by the protrusions Pe2 of the lower layer shown in

Fig. 6. As a result, the resonant frequency of the even

10   mode decreases, thereby creating a gap from the resonant

frequency of the odd modeand coupling the TE01δ_x mode and

the TE01δ_y mode.

On the other hand, Fig. 7(C) shows electric flux

density distribution of two coupling modes (TM coupling

15   modes) by the TM01δ_x mode and the TM01δ_y mode. (C) and (D)

show an even-mode electric flux density distribution and an

odd-mode electric flux density distribution, respectively.

Here, the protrusions Pe1 operate to increase the effective

dielectric constant of the part through which an odd-mode

20   electric flux passes. This also applies to the operation

provided by the protrusions Pe2 disposed on the lower layer.

Accordingly, the resonant frequency of the odd mode

decreases, thereby creating a gap from the resonant

frequency of the even mode and coupling the TM01δ_x mode and

25   the TM01δ_y mode.

15

However, protrusions Pc are disposed on the middle
layer portion of the dielectric core 1 shown in Fig. 6.
These protrusions Pc protrude in the 90°-different
directions around an z-axis with respect to the protruding
5   directions of the upper layer protrusions Pe1 and the lower
layer protrusions Pe2. These protrusions Pc operate in the
direction to decrease the resonant frequency of the even
mode of the TM coupling mode, contrary to the case shown in
Figs. 7(C) and 7(D). As a result, it is possible to make
10   the resonant frequencies of the even mode and the odd mode
of the TM coupling mode equal by determining the amounts of
the protrusions Pe1, Pe2, and Pc. That is to say, it is
possible to restrain the coupling between the TM01δ_x mode
and the TM01δ_y mode. Although the protrusions Pc of the
15   dielectric core 1 also give some influence on the TE
coupling mode, the influence is less than that on the TM
coupling mode, because the electric flux density of the TE
coupling mode is relatively higher in the upper part and the
lower part than in the middle part of the dielectric core.
20   Accordingly, the protrusions Pc have almost no influence on
the amount of coupling between the TE01δ_x mode and the
TE01δ_y mode.

Taking an advantage of this effect, the amount of the
coupling between the TE01δ_x mode and the TE01δ_y mode can be
25   determined independently of the coupling between the TM01δ_x

16

mode and the TM01δ_y mode by determining the amount of the protrusions Pe1, Pe2, and Pc of the dielectric core 1.

Here, examples of the changes of the resonant frequency and coupling coefficient of each resonant mode when the amount of the protrusions of the protruding portions disposed at the intersection between the x-direction part and y-direction part of the dielectric core 1 are shown in Figs. 8 and 9. Fig. 8(C) is an example where protrusions P of the dielectric core are formed in the same directions, as shown in Fig. 8(A) and 8(B), in any of the upper layer, the middle layer, and the lower layer of the dielectric core 1, and the amount of protrusions is changed. Here, KM denotes a coupling coefficient between the TM01δ_x mode and the TM01δ_y mode; KE denotes a coupling coefficient between the TE01δ_x mode and the TE01δ_y mode; TEo denotes a frequency of the odd mode of the TE coupling mode; TEe denotes a frequency of the even mode of the TE coupling mode; TMo denotes a frequency of the odd mode of the TM coupling mode; TMe denotes a frequency of the even mode of the TM coupling mode.

As described above, as the length (the amount of protrusion is expressed by the length of a side) of the protrusion P increases, the amount of coupling of the TE modes with each other increases as well as the amount of coupling of the TM modes with each other simultaneously.

17

Fig. 8(D) shows a characteristic in the situation where the protrusions P protrude in the same direction, as shown in Fig. 8(A) and 8(B), in the upper layer and the lower layer of the dielectric core 1, whereas the protrusions P in
5   the middle layer of the dielectric core 1 are formed at 90° different directions so that the KM becomes substantially zero. In (C), as the amount of the protrusions of the protrusion P of the dielectric core 1 increases, the resonant frequency of any of TEx, TEy, TMx, and TMy
10 decreases. In contrast, in (D), the frequencies of the TMo and TMe become almost constant. That is to say, the TM01δ_x mode and the TM01δ_y mode do not couple.

Fig. 9 shows an example where, as shown in (A) and (B), protrusions P are disposed at the 180° rotationally opposite
15 positions of the dielectric core 1 around the z-axis (in the direction perpendicular to the page surface) and subsidences S are disposed at the 90° rotational positions around the z-axis. (C) of Fig. 9 shows a characteristic in the case where protrusions P and subsidences S are disposed on any of
20 the upper layer, the middle layer, and the lower layer of the dielectric core 1 in the same directions. (D) shows a characteristic in the case where protrusions P and subsidences S of the upper and the lower layers of the dielectric core 1 are disposed in the same directions,
25 whereas those of the middle layer are disposed at the 90°

18

different directions, and the amount of the protrusions of the protrusion P and the amount of the subsidences of the subsidence S on the middle layer are determined such that the KM becomes substantially zero.

By forming the protrusions and the subsidences in this manner, KE can be made large as shown in (D), and TEe decreases as TEo increases. Accordingly, the coupling coefficients of both modes can be determined while keeping each of the frequencies of the basic modes (the $TE01\delta\_x$ mode and the $TE01\delta\_y$ mode) substantially constant. Thus, it becomes easy to adjust only the coupling coefficient independently of the resonant frequency.

Fig. 10 is an example in which a dielectric filter consisting of the four-stage resonators utilizing the above-described four resonant modes is constructed. (A) is a plan view with the top surface of the cavity is removed; (B) is a front view with the near-side wall surface of the cavity 2 removed. In Fig. 10, the dielectric core 1 is fixed by adhesion to the central part of the bottom surface of the cavity 2 through a support table 3 having a low dielectric constant. Thus, the dielectric core 1 is disposed substantially at the center of the cavity 2. Coaxial connectors 5a, 5b are attached to the cavity 2, and the central conductor thereof projects into the inside of the cavity 2 as input/output probes 4a, 4b. The probe 4a is

19

coupled, through electric field, to the $TM01\delta\_x$ mode whose

electric flux mainly passes the dielectric core 1 in the x

direction. The probe 4b is coupled, through electric field,

to the $TM01\delta\_y$ mode whose electric flux mainly passes the

5   dielectric core 1 in the y direction.

The coupling between the $TM01\delta\_x$ mode and the $TE01\delta\_y$

mode and the coupling between the $TE01\delta\_x$ mode and the

$TM01\delta\_y$ mode shown in Fig. 5 are performed by displacing the

height of the middle-layer part Lb having a high TM mode

10   electric flux density of the dielectric core 1 upward or

downward from the middle height. That is to say, the

balance of the electric field strength of the $TM01\delta\_x$ mode

and the $TM01\delta\_y$ mode in the vertical direction collapses,

and thus energy moves from the $TM01\delta\_x$ mode to the $TE01\delta\_y$

15   mode to produce the coupling between the both modes.

Similarly, energy moves from the $TE01\delta\_x$ mode to the $TM01\delta\_y$

mode to produce the coupling between the both modes.

In this manner, the dielectric resonator device

operates as a dielectric filter that is equipped with the

20   four-stage resonators and has a band-pass characteristic.

In this regard, the center of the electric flux

distribution of the $TM01\delta\_x$ mode and the $TM01\delta\_y$ mode can

also be displaced upwardly or downwardly by displacing the

position of the probes 4a, 4b shown in Fig. 10 in the

25   vertical direction (the z-axis direction) upwardly or

20

downwardly from the middle height of the dielectric core 1,
thereby coupling the TE01δ_y mode and the TE01δ_x mode.

Next, the structure of a dielectric filter according to
a second embodiment is shown in Fig. 11. Here, protrusions

5   Pe1, Pe2 for the TE coupling of the dielectric core 1 are
fillet-shaped. Also, protrusions Pc for restraining the TM
coupling are fillet-shaped. In this regard, portions which
do not protrude positively (90° rotated positions of Pe1,
Pe2, and Pc around the z-axis) are also fillet-shaped such

10   that the dielectric core 1 becomes difficult to crack. The
structure is the same as that shown by the first embodiment
for the other portions. Accordingly, as in the first
embodiment, the dielectric resonator device operates as a
dielectric filter that is equipped with the four-stage

15   resonators and has a band-pass characteristic.

Figs. 12 and 13 are diagrams illustrating the
configuration of a dielectric filter according to a third
embodiment. (A) of Fig. 12 is a plan view of the dielectric
core 1 in the cavity 2 and (B) is a front view of the same

20   dielectric core 1. This dielectric core 1 has a structure
equal to the structure in which the middle-layer part Lb of
the dielectric core 1 shown in Fig. 10 shifted to the
lowermost to eliminate the lower-layer part Lc in order to
have a two-layer structure consisting of an upper-layer part

25   La and a lower-layer part Lb'. Accordingly, the probes 4a,

21

4b are also disposed in the central part of the lower-layer part Lb' of the dielectric core 1. Even with this two-layer structure, the TE01δ_x mode and the TE01δ_y mode can be coupled by the protrusion of the protrusions Pe for TE

5 coupling, and the coupling between the TM01δ_x mode and the TM01δ_y mode can be restrained by the protrusion of the protrusions Pc for restraining the TM coupling. Accordingly, the dielectric resonator device also operates as a dielectric filter consisting of the four-stage resonators

10 and having a band-pass characteristic.

In the example shown in Fig. 12, protrusions Pm are disposed on the dielectric core 1 for the TM01δ mode. However, the excitation and the external coupling of the TM01δ mode can be performed without disposing dielectric

15 core protrusions Pm, as shown in Fig. 13. At that time, as shown in Fig. 13, it is possible to increase independence in the dielectric core 1 of the electric flux of the TM01δ mode passing through the dielectric core 1 by disposing a flat surface part, which faces the dielectric core 1, on each of

20 the probe 4a and 4b.

Figs. 14 and 15 show the structure of a dielectric filter according to a fourth embodiment. In both figures, (A) is a plan view of the dielectric core 1 inside the cavity 2 and (B) is a front view thereof. The dielectric

25 core 1 used in the dielectric filter according to the fourth

22

embodiment has an outer cubic shape with subsidences Se on

its upper layer part La and subsidences Sc on its lower-

layer part Lb'. The subsidences Se formed on the upper-

layer part La of the dielectric core 1 creates a difference

5   in the resonant frequencies of the even mode and the odd

mode of the TE coupling mode, thereby coupling the TE01δ_x

mode and the TE01δ_y mode. Also, the subsidences Sc formed

on the lower-layer part Lb operates to suppress the shift of

the frequencies of the even mode and the odd mode of the TM

10   coupling mode that is caused by the presence of the above-

described subsidences Se. Accordingly, it is possible to

suppress the coupling between the TM01δ_x mode and the

TM01δ_y mode by balancing the subsidences Se and Sc.

The example shown in Fig. 15 is the case where the

15   protrusions Pm for the TM01δ mode formed on the dielectric

core 1 in Fig. 14, is eliminated. Using such a dielectric

core, the dielectric resonator device operates as a

dielectric filter, in the same manner, in which the four-

stage resonators are coupled in sequence and which has a

20   band-pass characteristic.

Figs. 16 and 17 are diagrams illustrating the structure

of a dielectric filter according to a fifth embodiment. The

dielectric core 1 used in this dielectric filter is equal to

a structure in which a dielectric core 1 shown in Fig. 14 is

25   modified to have a cylindrical shape. That is to say, the

23

dielectric core 1 has a substantially cylindrical shape as a whole, forming subsidences Se for the TE coupling on the upper-layer part La, and subsidences Sc for restraining the TM coupling on the lower-layer part Lb'. Also, Fig. 17 is

5   equal to a structure in which the dielectric core protrusions Pm in Fig. 16 are removed. Even using such forms, the dielectric resonator device also operates as a dielectric filter consisting of four-stage resonators and having a band-pass characteristic.

10   Fig. 18 is a diagram illustrating the configuration of a dielectric filter according to a sixth embodiment. In this example, the dielectric core 1 is cross-shaped in its plan view, and forms subsidences Se for the TE coupling on the upper-layer part La, and subsidences Sc for restraining

15   the TM coupling on the lower-layer part Lb'. Since the subsidences Se cause a difference in the resonant frequencies of the even mode and the odd mode of the TE coupling mode, the $TE01\delta\_x$ mode and the $TE01\delta\_y$ mode are coupled by subsidences Se. Also, the subsidences Sc formed

20   on the lower-layer part Lb operate to restrain the shift of the frequencies of the even mode and the odd mode of the TM coupling mode. Accordingly, it is possible to restrain the coupling between the $TM01\delta\_x$ mode and the $TM01\delta\_y$ mode by balancing the subsidences Se and Sc.

25   Using such a dielectric core, the dielectric resonator

24

device also operates, in the same manner, as a dielectric filter in which the four-stage resonators are coupled in sequence and which has a band-pass characteristic.

Fig. 19 is a diagram illustrating the configuration of a dielectric filter according to a seventh embodiment. In this example, holes He for the TE coupling are formed in the upper layer part of the dielectric core 1 and holes Hc for restraining the TM coupling are formed on the lower-layer part. In this manner, it is possible to cause a difference in effective dielectric constants of the individual parts through which the even-mode and odd-mode electric flux of the TE coupling mode pass and to make the effective dielectric constants of the individual parts through which the even-mode and the odd-mode electric flux of the TM coupling mode pass substantially equal, thereby coupling the TE01δ_x mode and TE01δ_y mode without coupling the TM01δ_x mode and TM01δ_y mode.

Fig. 20 is a diagram illustrating the configuration of a dielectric filter according to an eighth embodiment. The dielectric core 1 used here is the same dielectric core 1 shown in Fig. 12. However, within the cavity 2, the dielectric core 1 is rotatedat 45° around the z-axis. Also, in connection with this, a probe 4a is disposed near the end of the x-direction part 1x of the dielectric core and a probe 4b is disposed near the end of the y-direction part 1y

25

of the dielectric core. Note that although the portions of the dielectric core denoted by 1x and 1y are not oriented in the x-direction and y-direction, respectively, the same reference numerals are used in order to correspond to the

5   reference numerals shown in Fig. 12. Here, the TM mode whose electric flux mainly passes through the 1x portion of the dielectric core 1 can be denoted as the $TM01\delta\_(x + y)$ mode, the TM mode whose electric flux mainly passes through the 1y portion of the dielectric core 1 can be denoted as

10   the $TM01\delta\_(x - y)$ mode. Further, the TE mode whose electric field rotates in the 1x portion can be denoted as the $TE01\delta\_(x + y)$ mode, and the TE mode whose electric field rotates in the 1y portion can be denoted as the $TE01\delta\_(x - y)$ mode.

15   The $TE01\delta\_(x + y)$ mode and the $TE01\delta\_(x - y)$ mode can be coupled by the protrusion of the protrusions Pe for the TE coupling, and the coupling between the $TM01\delta\_(x + y)$ mode and the $TM01\delta\_(x - y)$ mode due to the above-described protrusions Pe can be suppressed by the protrusion of the

20   protrusions Pc for the TM coupling suppression. Accordingly, the dielectric resonator device of this example also operates as a dielectric filter consisting of the four-stage resonators and having a band-pass characteristic.

         Next, the configuration of a composite dielectric

25   filter is shown in Fig. 21 as a ninth embodiment. Here, the

26

portions denoted as Rtx and Rrx include the dielectric filter shown in Fig. 20, respectively. Probes 4tx, 4rx respectively couple with one of the TM01δ modes of the resonators Rtx, Rrx through an electric field. Also, probe

5   4ant couples with the other TM01δ mode of the resonators Rtx, Rrx, respectively. Here, the probe 4ant performs a phase adjustment such that a transmission signal does not sneak in the reception filter side and a reception signal does not sneak in the transmission filter side. Here, by setting the

10 frequency of each resonant mode, the composite dielectric filter operates on the whole as a transmitter/receiver with a coaxial connector 5tx as a transmission-signal input part, 5rx as a reception-signal output part, 5ant as an antenna connection part, Rtx as a transmission filter, and Rrx as a

15 reception filter.

Next, the configuration of a communication apparatus according to a tenth embodiment is shown in Fig. 22 as a block diagram. Here, the transmitter/receiver shown in Fig. 21 is used for a duplexer. A transmission circuit and

20 a receiving circuit are connected to the transmission-signal input port and the reception-signal output port of the duplexer, respectively. An antenna is connected to an antenna port. In this manner, a communication apparatus equipped with a multimode dielectric resonator device

25 according to the present invention is constituted.

27

According to this present invention, a difference in frequency arises between the even-mode and the odd-mode, which are the two coupling modes of the first and the second TE01δ modes, thereby causing the coupling of the first and

5   the second TE01δ modes. Also, no difference in frequency arises between the even-mode and the odd-mode, which are the two coupling modes of the first and the second TM01δ modes or TM011 modes, thereby causing no coupling of the first and the second TM01δ modes or TM011 modes among themselves.

10 That is to say, the coupling of the first and the second TE01δ modes themselves can be set independently of TM modes.

Also, according to this invention, with regard to the even mode and the odd mode of the TE coupling modes, a difference is created in the amount of a protrusion or the

15 amount of a subsidence of the dielectric core portions having electric flux passing therethrough and a subsidence or a protrusion that cancels the frequency changes, caused by said difference, of the even mode and the odd mode of the TM coupling modes is provided in the dielectric core portion

20 having a relatively low electric flux density of the TE coupling mode. Thus, a frequency change of the even mode and the odd mode of the TM coupling mode, which arises from the difference in the amount of protrusion or the amount of subsidence of the dielectric core disposed on the position

25 having a high electric flux density of the TE coupling mode,

28

is canceled, and the coupling of the first and the second TM01δ or TM011 modes themselves can be prevented.

Also, according to this invention, the first and the

second TM01δ modes or TM011 modes and the first and the

5   second TE01δ modes are coupled, respectively, by displacing a center of electric flux density distribution of the first and the second TM01δ modes or the first and the second TM011 modes upwardly or downwardly in planes perpendicular to the directions of the electric fields of the first and the

10   second TM01δ modes or the first and the second TM011 modes. At this time, since the coupling does not arise between the first and the second TM01δ modes or the TM011 modes themselves, the first TM01δ mode or TM011 mode→the first TE01δ mode→the second TE01δ mode→the second TM01δ mode or

15   TM011 mode are coupled in sequence, thereby operating as four-stage resonators.

Also, according to this invention, a dielectric filter can be used as a small-sized band-pass filter by providing: a multimode dielectric resonator device operating as the

20   four-stage resonators described above; and external coupling means for external coupling of the first-stage and the last-stage resonators, respectively, of the four-stage resonators.

Also, according to this invention, by providing two sets of the dielectric filters described above and sharing

25   one of the external coupling means of each of the dielectric

29

filters, for example, the dielectric filter can be used as a small-sized transmitter/receiver having one of the filters as a transmission filter, the other of the filters as a reception filter, and the shared external coupling means as

5   an antenna port.

Also, according to this invention, a small-sized communication apparatus having a predetermined high-frequency circuit characteristic can be constituted by providing the above-described dielectric filter or composite

10   dielectric filter in a high-frequency circuit portion.